

# Towbar Wiring Harness Fitting Instructions

## TOYOTA HILUX UTE & CAB CHASSIS 10/15 - ON



#### **CAB CHASSIS**

- 1. Unplug the 6 way connector behind the RHS tail light.
- 2. Find the plugs on the harness marked RHS and connect into plugs on car from step 1.
- 3. Follow the same process for the LHS with the remaining two grey plugs.
- 4. Using cable ties secure the wiring harness to meet the required length.
- 5. Mount ECU using double side tape attached.
- 6. Run the Power Wire along the chassis to the battery. Secure cable with zipties or similar (not supplied). Keep a safe distance from heat and sharp edges.
- 7. Attach Power wire to the fuse holder supplied.
- 8. Attach fuse holder to positive terminal on the battery.
- 9. Fit the required socket to the wiring harness and mount the plug to desired position.
- 10. Insert fuse into fuse holder.
- 11. Test towbar wiring with a trailer testing box.





# Towbar Wiring Harness Fitting Instructions

## TOYOTA HILUX UTE & CAB CHASSIS 10/15 - ON

# PART NO.

#### UTE

- 1. Remove RHS tail lights.
  - Lower rear tailgate
  - Undo x2 10mm head bolts from side of light
  - Carefully remove light
- 2. Unplug the 6 way connector behind the RHS tail light.
- 3. Find the plugs on the harness marked RHS and connect into plugs on car from step 2.
- 4. Follow the same process for the LHS with the remaining two grey plugs.
- 5. Using cable ties secure the wiring harness to meet the required length.
- 6. Mount ECU using double side tape attached.
- 7. Run the Power Wire along the chassis to the battery. Secure cable with zipties or similar (not supplied). Keep a safe distance from heat and sharp edges.
- 8. Attach Power wire to the fuse holder supplied.
- 9. Attach fuse holder to positive terminal on the battery.
- 10. Fit the required socket to the wiring harness and mount the plug to desired position.
- 11. Insert fuse into fuse holder.
- 12. Test towbar wiring with a trailer testing box.